

ATP Cummins - Leroy Somer Series



ATP72-CMMS/LS

Main Features

T	Three-phase	Hz	50 Hz
	Diesel		1500 r.p.m.
	Cummins / 4BTA3.9-G2	V	230V/400V
	Leroy somer / TAL-A44-C	cosφ	0,8
	DSE6110/20		ABB 4x160A

Standby Power (STP)	72 kVA	57 kW
Continuous Power (PRP)	65 kVA	52 kW
Continuous Power (COP)	- kVA	- kW

Soundproof

Length (L)	2450 mm	
Height (H)	1000 mm	
Width (W)	1570 mm	
Weight	1400 kg	
Daily deposit	145 Lts	
		50 Hz
Sound pressure level @1m		68 dB(A)

Installation in room

Exhaust System	50Hz		
	COP	PRP	STP
Maximum back pressure (kPa)	10		
Intake air alarm temperature (°C)	13,5		
"Maximum intake air restriction with heavy-duty air filter Dirty Element (kPa) Clean Element (kPa)"	-		
Max. exhaust pipe diameter (mm)	75		

Fuel System	50Hz		
	COP	PRP	STP
Maximum restriction on lift pump (KBar)	-	-	102
Maximum fuel inlet temperature (°C)	508		
Total drainage flow (L/hr)			30

Electrical system	50Hz		
	COP	PRP	STP
Starter motor (Vdc)	24		
Battery charging system, negative ground (A)	40		
Maximum allowable starting circuit resistance (Ω)	0,002		
"Minimum recommended battery capacity — Cold soak @ 0 to 32°F (-18 to 0°C)"	312		

Engine specifications

General specifications	50 Hz
Model	4BTA3.9-G2
Emissions	Not applicable
Operating method	Four Times
Fuel type	Diesel
Refrigeration system	Liquid (water + 50% antifreeze)
Aspiration system	Turbocharged
Injection system	Direct
Number and arrangement of cylinders	4 in-line
Displacement (L)	3.90
Cylinder bore (mm)	102
Cylinder stroke (mm)	120
Compression ratio	18.0:1
Regulation	Electronic
Rotational speed	1500
Coolant capacity (L)	7,2
Gross power COP (kWm)	-
Gross power PRP (kWm)	58
Gross power STP (kWm)	64
Oil capacity (L)	10,9
Net power COP (kWm)	-
Net power PRP (kWm)	-
Net power STP (kWm)	-



Consumptions		50 Hz	
Fuel consumption	Burden	lt/h	g/kWh
STP	100%	16,5	213
PRP	100%	14,9	212
	75%	11,4	217
	50%	8,1	230
	25%	4,8	275
Min. allowable fuel flow to the fuel pump (L/h)		16,5	
Reference conditions			
Temperature (°C)		25	
Atmospheric pressure (kPa)		100	
Starting system			
Voltage (V)		24	
Standard thermostat range (°C)		82-95	

Alternator specifications

General specifications	
Model	TAL-A44-C
Number of phases	Three-phase
Protection	IP23
Isolation	H
Heating	H
IEC Waveform = THF	<2,0%
NEMA Waveform = TIF	<50
Excitation system	SHUNT/AREP+
AVR Model	R120/R180



Overspeed: rpm	2250
Voltage regulation: (steady state)	+/- 1.0%
Air flow rate 60 Hz (m3/s)	0,12
Radio interference:	Deletion in accordance with the standard European EN61000-6
AREP+ Short circuit current	2.7 In: 5 seg.

Starter Battery



Battery voltage	
Battery Capacity	
Amount	
Battery type	Maintenance-free, sealed lead-acid type

Certifications



Control Panel



Generator	DSE6110/20
Tension (F-F / F-N)	★ / ★
Intensity	★
Frequency	★
RMS values	★
Generator phase sequence	★
Generator ground current [1]	■
Number of events registered	250
Integrated clock	★
PIN protection	★
kWh, kVAh, kVAh, kVAh, cos Ø	★
Synchoscope (m)	☒
Number of available departures [2]	6
Engine running hours	★
Alarm indication on LCD	★
Total number of LED indicators	8
No. of LED alarms	☒
Acoustic alarm signaling	■
Programmer	★
Fuel level	★
Engine	DSE6110/20
Engine speed	★
Low oil pressure protection	★
Oil pressure reading [3]	■
High engine temperature protection	★
Engine temperature reading[3]	■
Battery voltage	★
Battery Intensification [4]	■
Fuel consumption [5]	★
Low water level in radiator [6]	■
Scheduled maintenance for engine	★
Communication	DSE6110/20
USB Type B Female Port (Max. 6m)	★
[7] USB Type A Female Port (n)	☒
CAN port (Max. 40m)	★
PLC function	★

Grid	DSE6110/20
Tension (F-F / F-N)	★
Intensity [1]	☒
Frequency	★
kVA,kW, cos Ø (a)	☒
Network-group switching control	★
Protections and alarms	DSE6110/20
High/low battery voltage	🔔
Battery charging alternator failure	🔔
Stop failure	🔔 / ⌛
Boot failure	🔔 / ⌛
Low fuel level	🔔 / ⌛
Overload	🔔 / ⌛
Ground fault	🔔 / ⌛
Asymmetry between phases	🔔 / ⌛
Maintenance	🔔 / ⌛
High/Low Generator Frequency	🔔 / ⌛
Engine overspeed	🔔 / ⌛
Low engine speed	🔔 / ⌛
Surge	🔔 / ⌛
Low voltage in generator	🔔 / ⌛
ECU Alert (if applicable)	🔔 / ⌛
Low oil pressure	🔔 / ⌛
Low water level in radiator [f]	🔔 / ⌛
High engine temperature	🔔 / ⌛
Fuel leak/theft	🔔
Applications	DSE6110/20
Automatic or manual start	★
Remote start by dry contact NA	★
Automatic due to network failure	★
Alternation with distributed time	☒
Multi-generators in synchronism with load (Max 32 generators) (m)	☒
Generator-grid in synchronism and with load sharing (1 generator and 1 grid) (m)	☒
Optional Expansions	DSE6110/20
DSE2130 (8 digital inputs) I G-IOM (8 digital inputs/outputs + 4 analog inputs) G-08 (8 ent. dig.)	★
DSE2157 I -RB8 G-06 (8 relay outputs)	★
DSE2548 IGL-RA15 - (expansion with 8 Additional LEDs	★
DSE2510/20 (mirror controller, max distance 1km)	★
Rules	
Working temperature	-30 ~> 70°C
Protection index (when mounted with sealing gasket)	IP65
Maximum humidity level (for 48 h)	93% / 40°C

Legend

★	Available
■	Optional
☒	Not available
🔔	Warning alarm
⏸	Stop alarm
[1]	Need an additional IT
[2]	Number of outputs available for standard configuration. Outputs do not include relays or additional wiring to terminals.
[3]	If the information is not provided by the engine ECU, an additional sensor needs to be included.

[4]	Needs an additional ammeter
[5]	If the information is provided by the engine ECU
[6]	Requires an additional sensor
[7]	Need to include an additional IL-NT-S-USB module
[8]	Need to include an additional IL-NT-RS232-485 module
[9]	DeepSea: Needs to include an additional DSE891 module/ComAp: Needs to include an additional IB-LITE module
[10]	DeepSea: Needs to include an additional DSE890 module/ComAp: Needs to include an additional IL-NT-GPRS module
[11]	DeepSea: Needs to include an additional DSE892 module/ComAp: Needs to include an additional IB-LITE module

Emergency Standby Power (ESP)

Emergency standby power is the maximum power available to a variable load during a main power grid failure. The average load factor over 24 hours of operation must not exceed 70% of the motor's ESP rated power. Typical motor operating hours are 200 hours per year, with a maximum usage of 500 hours per year.

This includes an annual maximum of 25 hours per year at the ESP power rating. Overload capability is not permitted. The motor must not be used for sustained utility parallel applications.

Main Power (PRP)

Prime Power is the maximum power available for unlimited hours of use in a variable load application. The average load factor must not exceed 70% of the motor's PRP rating during any 24-hour period. A 10% overload capability is available; however, it is limited to 1 hour within each 12-hour period.

1. All ratings are based on operating conditions according to ISO 8528-1, ISO 3046, DIN6271. Performance tolerance $\pm 5\%$.
2. Test conditions: 100 kPa, 25°C air inlet temperature, 30% relative humidity, with fuel density of 0.84 kg/L. Derating may be required for conditions outside these, contact factory for details.
3. Power output curves are based on engine operation with fuel system, water pump and lubricating oil pump; battery charging alternator, fan and optional equipment are not included.